

# DAO-D4-0X2

## Dante 2CH Analog Output Dongle



All Rights Reserved

Version: DAO-D4-0X2\_2023V1.2

### Product Introduction

Thanks for choosing the DAN-D4. It connects to your Dante network and supports Analog 0X2 channels audio, allowing analog amplifier to your Dante audio network.

### Features

- Plug and Play
- 24-bit audio support
- 0X2 audio channels
- Supports 802.3af PoE

### Packing List

- 1x DAN-D4
- 1x User Manual

**Note:** Please contact your distributor immediately if any damage or defect in the components is found

### Panel Description



- ① **RJ45:** Dante network communication port. Green steady light indicates system ready; yellow flashing light indicates link/data traffic. The green light will flash to identify the device when clicking the Dante Controller "Identify" button (an eye-shaped symbol) on the host computer.
- ② **XLR:** 2 x XLR female, connect output device

## Technical Specification

<b>Audio</b>	
Max signal level	+18 dBu
Output Gain	-6 dBu
Frequency Response	20Hz to 20kHz(-/+0.5dB)
Impedance	150 Ohm balanced 75 Ohm unbalanced
Dynamic Range	>100 dB
Signal to Noise Ratio	>100 dB
THD	<0.01% @+4 dBu
<b>Dante</b>	
Sample Rate	44.1kHz, 48kHz, 96kHz
Bit Depth	24

Dante Device latency	1,2 or 5ms (configurable using Dante Controller)
Model Name	Analog 0X2
<b>General</b>	
Operation Temperature	-5 to +55°C (+23° to +131°F)
Storage Temperature	-25 to +70°C (-13° to +158°F)
Power	802.3af PoE
Power Consumption	2.6W(Max)
Dimension (W*H*D)	30 x 28 x 114 mm
Cable length	300mm
Net Weight	145g

